

COMPAX200M, COMPAX500M, COMPAX1500M Pinout Lists

X1 - Motor/Brake Connections 7-Pin Screw Terminal Connector		
Pin #	Type	Signal
1	Phase U	U
2	Phase V	V
3	Phase W	W
4	Brake Input	BR-
5	Brake Output	BR+

X2 - Power Intermediate Loop, 6-Pin Connector			
Pin #	Signal	Pin #	Signal
1	PE	4	PE
2	LS+	5	LS+
3	LS-	6	LS-

X3 - Control Voltage, Screw Terminal	
Pin #	Signal
1	24V
2	0V

X6 - RS-232, 9-Pin Removable Connector	
Pin #	Signal
1	NC
2	RXD
3	TXD
4	DTR
5	GND
6	DSR
7	RTS
8	CTS
9	+5V

X13 - Encoder, 15-Pin D Connector		
Pin #	Type	Signal
1	Ground	Housing
2	Input	N2
3	Input	B2
4	Input	A2
5	Input	N1
6	Input	B1
7	Input	A1
8	Output	+5V
9	Input	N2-
10	Input	B2-
11	Input	A2-
12	Input	N1-
13	Input	B1-
14	Input	A1-
15		GND

X8 - Input/Output, 16-Pin Removable Connector	
Pin #	Signal
1	Input
2	Input
3	Input
4	Input
5	Input
6	Input
7	Input
8	Input
9	Output
10	Output
11	Output
12	Output
13	Output
14	Output
15	Output
16	Output

X9 - Emergency Stop and Standby, 7-Pin Removable Connector		
Pin #	Type	Signal
1	Output	+24V
2	Return	GND
3		Reserved
4		Reserved
5	Output	24V
6	Input	24V
7		Emergency Stop Housing

X10 - Input/Output, 16-Pin Removable Connector	
Pin #	Signal
1	Input
2	Input
3	Input
4	Input
5	Input
6	Input
7	Input
8	Input
9	Output
10	Output
11	Output
12	Output
13	Output
14	Output
15	Output
16	Output

X18 - Fan, Removable Screw Terminal		
Pin #	Type	Signal
1		24V
2		0V

X11 - DA Monitors, 7-Pin D Connector		
Pin #	Type	Signal
1	Output	+24V
2	Output	GND
3	Output	override
4	Input	DA-CH2
5	Input	DA-CH3
6	Input	override(-)
7		Shield

X12 - Resolver, 15-Pin D Connector		
Pin #	Type	Signal
1	Ground	Housing
2		NC
3		NC
4	Output	REF-
5	Input	SIN-
6		NC
7		GND
8		NC
9	Input	+5V
10	Input	TEMP
11	Input	COS-
12	Input	COS+
13	Input	SIN+
14	Output	REF+
15		NC

X14 and X15 - HEDA, 9-Pin D Connector			
Pin #	Signal	Pin #	Signal
1	NC	5	TXD
2	RXC	6	RXC-
3	TXC	7	TXC-
4	RXD	8	RXD-
		9	TXD-

X16 - Absolute Encoder, 9-Pin D Connector			
Pin #	Signal	Pin #	Signal
1	T-	5	GND
2	NC	6	T+
3	D-	7	NC
4	NC	8	D+
		9	+24V

X17 - DA Monitor/Indicators, 9-Pin D Connector		
Pin #	Type	Signal
1	Output	DA-CH0
2	Output	DA-CH1
3		Shield
4	Supply Indicator	GND 24V
5	Supply Indicator	+24V
6	Reference	GND
7	Input	Sig-MN
8	Input	Sig-E2
9	Input	Sig-E1

Ordering Information	
Part No.	Description
Drives:	
COMPAX200M	6.5A Continuous Drive
COMPAX500M	11.5A Continuous Drive
COMPAX1500M	25A Continuous Drive
Motors:	
HDY70C4-44S	70 mm Brushless motor w/resolver
HDY92E4-44S	92 mm Brushless motor w/resolver
HDY115A6-88S	115 mm Brushless motor w/resolver
HDY115C6-88S	115 mm Brushless motor w/resolver
HDY142C6-88S	142 mm Brushless motor w/resolver
HDY142G6-88S	142 mm Brushless motor w/resolver
HMBR190E6-88S	190 mm Brushless motor w/resolver
HMBR190J6-260S	190 mm Brushless motor w/resolver
Motor-to-drive cables:	
MOK42	Motor cable for HDY70 through HDY115
MOK43	Motor cable for HDY142
MOK21	Motor cable for HMBR190
Resolver-to-drive cables:	
REK32	Resolver cable for HDY70 through HDY142
REK14	Resolver cable for HMBR190
Standard lengths available from 2.5 meters to 50 meters. Please call factory for additional ordering information.	

For More Information on CE-Marked Digital Servo Systems, Call 1-800-358-9070 Today.