

Section 7. PROGRAMMING EXAMPLES

7.1. COMPUMOTOR PLUS PROGRAMMING EXAMPLES

All Compumotor Plus command identifiers begin with a capital letter and end with either a space or a carriage return. Commands may be preceded by a device address number.

7.2. COMMON UTILITY COMMANDS

Command: LD3

Disable the limit switch functions. This allows motion with no limits connected.

Command: ^H

Backspace (control-H). Hold the control key down and press "H". This command causes the Compumotor Plus to ignore the last character entered.

Command: Z

Master Reset. This is automatically performed at power-up.

Command: 1RSE

Report servo errors. Normally reports *NO_ERRORS.

PROGRAMMING EXAMPLES
